

PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Key Features

- Case dimensions
50.8 x 25.4 x 11.9 mm (2 x 1 x 0.47 in)
- High efficiency, typ. 89% at Full load
- Meets safety requirements according to IEC/UL 62368-1

General Characteristics

- Output over voltage protection
- Input under voltage shutdown
- Over temperature protection
- Output short-circuit protection
- Remote control
- Output voltage adjust function



Safety Approvals



Design for Environment



Meets requirements in high-temperature lead-free soldering processes.

Contents

Ordering Information	2
General Information	2
Safety Specification	2
Absolute Maximum Ratings	4
Electrical Specification	
12V, 2.5A / 30W	PKE 3313A PI 5
EMC Specification	8
Operating Information	9
Thermal Consideration	11
Connections	12
Mechanical Information	13
Soldering Information	14
Delivery Information	14
Product Qualification Specification	15

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Ordering Information

Product program	Output
PKE 3313A PI	12 V, 2.5 A / 30 W

Product number and Packaging

PKE 3313A PI n ₁	
Options	n ₁
Remote Control logic	o

Options	Description
n ₁	Negative * P Positive

Example negative logic product with tray packaging would be PKE 3313A PI.

* Standard variant (i.e. no option selected).

General Information

Reliability

The failure rate (λ) and mean time between failures (MTBF = $1/\lambda$) is calculated at max output power and an operating ambient temperature (T_A) of +25°C. Flex uses Telcordia SR-332 Issue 2 Method 1 to calculate the mean steady-state failure rate and standard deviation (σ).

Telcordia SR-332 Issue 2 also provides techniques to estimate the upper confidence levels of failure rates based on the mean and standard deviation.

Mean steady-state failure rate, λ	Std. deviation, σ
338 nFailures/h	209.50 nFailures/h

MTBF (mean value) for the PKE3312A series = 2.95 Mh.
MTBF at 90% confidence level = 2.6 Mh.

Compatibility with RoHS requirements

The products are compatible with the relevant clauses and requirements of the RoHS directive 2011/65/EU and have a maximum concentration value of 0.1% by weight in homogeneous materials for lead, mercury, hexavalent chromium, PBB and PBDE and of 0.01% by weight in homogeneous materials for cadmium.

Exemptions in the RoHS directive utilized in Flex products are found in the Statement of Compliance document.

Flex fulfills and will continuously fulfill all its obligations under regulation (EC) No 1907/2006 concerning the registration, evaluation, authorization and restriction of chemicals (REACH) as they enter into force and is through product materials declarations preparing for the obligations to communicate information on substances in the products.

Quality Statement

The products are designed and manufactured in an industrial environment where quality systems and methods like ISO 9000, Six Sigma, and SPC are intensively in use to boost the continuous improvements strategy. Infant mortality or early failures in the products are screened out and they are subjected to an ATE-based final test. Conservative design rules, design reviews and product qualifications, plus the high competence of an engaged work force, contribute to the high quality of the products.

Warranty

Warranty period and conditions are defined in Flex General Terms and Conditions of Sale.

Limitation of Liability

Flex does not make any other warranties, expressed or implied including any warranty of merchantability or fitness for a particular purpose (including, but not limited to, use in life support applications, where malfunctions of product can cause injury to a person's health or life).

© Flex 2017

The information and specifications in this technical specification is believed to be correct at the time of publication. However, no liability is accepted for inaccuracies, printing errors or for any consequences thereof. Flex reserves the right to change the contents of this technical specification at any time without prior notice.

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Safety Specification

General information

Flex Power DC/DC converters and DC/DC regulators are designed in accordance with the safety standards IEC 62368-1, EN 62368-1 and UL 62368-1 *Audio/video, information and communication technology equipment - Part 1: Safety requirements*

IEC/EN/UL 62368-1 contains requirements to prevent injury or damage due to the following hazards:

- Electrical shock
- Electrically-caused fire
- Injury caused by hazardous substances
- Mechanically-caused injury
- Skin burn
- Radiation-caused injury

On-board DC/DC converters, Power interface modules and DC/DC regulators are defined as component power supplies. As components they cannot fully comply with the provisions of any safety requirements without "conditions of acceptability". Clearance between conductors and between conductive parts of the component power supply and conductors on the board in the final product must meet the applicable safety requirements. Certain conditions of acceptability apply for component power supplies with limited stand-off (see Mechanical Information for further information). It is the responsibility of the installer to ensure that the final product housing these components complies with the requirements of all applicable safety standards and regulations for the final product.

Component power supplies for general use shall comply with the requirements in IEC/EN/UL 62368-1. Product related standards, e.g. IEEE 802.3af *Power over Ethernet*, and ETS-300132-2 *Power interface at the input to telecom equipment, operated by direct current (dc)* are based on IEC/EN/UL 60950-1 with regards to safety.

Flex Power DC/DC converters, Power interface modules and DC/DC regulators are UL 62368-1 recognized and certified in accordance with EN 62368-1. The flammability rating for all construction parts of the products meet requirements for V-0 class material according to IEC 60695-11-10, *Fire hazard testing, test flames – 50 W* horizontal and vertical flame test methods.

Isolated DC/DC converters & Power interface modules

The product may provide basic or functional insulation between input and output according to IEC/EN/UL 62368-1 (see Safety Certificate), different conditions shall be met if the output of a basic or a functional insulated product shall be considered as ES1 energy source.

For basic insulated products (see Safety Certificate) the output is considered as ES1 energy source if one of the following conditions is met:

- The input source provides supplementary or double or reinforced insulation from the AC mains according to IEC/EN/UL 62368-1.
- The input source provides functional or basic insulation from the AC mains and the product's output is reliably connected to protective earth according to IEC/EN/UL 62368-1.

For functional insulated products (see Safety Certificate) the output is considered as ES1 energy source if one of the following conditions is met:

- The input source provides double or reinforced insulation from the AC mains according to IEC/EN/UL 62368-1.
- The input source provides basic or supplementary insulation from the AC mains and the product's output is reliably connected to protective earth according to IEC/EN/UL 62368-1.
- The input source is reliably connected to protective earth and provides basic or supplementary insulation according to IEC/EN/UL 62368-1 and the maximum input source voltage is 60 Vdc.

Galvanic isolation between input and output is verified in an electric strength test and the isolation voltage (V_{iso}) meets the voltage strength requirement for basic insulation according to IEC/EN/UL 62368-1.

It is recommended to use a slow blow fuse at the input of each DC/DC converter. If an input filter is used in the circuit the fuse should be placed in front of the input filter. In the rare event of a component problem that imposes a short circuit on the input source, this fuse will provide the following functions:

- Isolate the fault from the input power source so as not to affect the operation of other parts of the system
- Protect the distribution wiring from excessive current and power loss thus preventing hazardous overheating

PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017


© Flex

Absolute Maximum Ratings

Characteristics		min	typ	max	Unit
T_{P1}	Operating Temperature	-40		+100	°C
T_S	Storage temperature	-55		+125	°C
V_I	Input voltage	9		36	V
V_{iso}	Isolation voltage (input to output test voltage)			1600	Vdc
V_{tr}	Input voltage transient (Tp 100 ms)			40	V
V_{RC}	Remote Control pin voltage (see Operating Information section)	0		8	V

Stress in excess of Absolute Maximum Ratings may cause permanent damage. Absolute Maximum Ratings, sometimes referred to as no destruction limits, are normally tested with one parameter at a time exceeding the limits in the Electrical Specification. If exposed to stress above these limits, function and performance may degrade in an unspecified manner.

Fundamental Circuit Diagram



PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Electrical Specification**PKE 3313A PI****12 V, 2.5 A / 30 W**

Typical values given at: TP1 = +25°C, VI = 24 V max IO, unless otherwise specified under Conditions.

Additional Cout = 4.7µF ceramic Cap. See Operating Information section for selection of capacitor types.

Characteristics		Conditions	min	typ	max	Unit
V _I	Input voltage range		9		36	V
V _{Ioff}	Turn-off input voltage	Decreasing input voltage	6.5	7.5	8.5	V
V _{Ion}	Turn-on input voltage	Increasing input voltage	8	8.5	9	V
C _I	Internal input capacitance			10		μF
P _O	Output power		0		30	W
η	Efficiency	50% of max I _O , V _I = 12 V		86		%
		max I _O , V _I = 12 V		88		
		50% of max I _O , V _I = 24 V		88		
		max I _O , V _I = 24 V		89		
P _d	Power Dissipation	max I _O		3.4	4	W
P _{li}	Input idling power	I _O = 0 A, V _I = 24 V		1.0		W
P _{RC}	Input standby power	V _I = 24 V (turned off with RC)		1.25		W
f _s	Switching frequency	0-100 % of max I _O	297.5	350	402.5	kHz

V_{OI}	Output voltage initial setting and accuracy	$T_{P1} = +25^\circ\text{C}$, $V_I = 24$ V, $I_O = 2.5$ A	11.88	12	12.12	V
V_O	Output adjust range	See operating information	10.8	12	13.2	V
	Output voltage tolerance band	0-100% of max I_O	11.856		12.144	V
	Idling voltage	$I_O = 0$ A	11.856		12.144	V
	Line regulation	max I_O		10	60	mV
	Load regulation	$V_I = 24$ V, 25-100% of max I_O		10	60	mV
V_{tr}	Load transient voltage deviation	$V_I = 24$ V, Load step 50-75-50% of max I_O , $di/dt = 100\text{mA}/\mu\text{s}$		±30	±200	mV
t_{tr}	Load transient recovery time			70	250	µs
t_r	Ramp-up time (from 10-90% of V_{OI})	100% of max I_O			20	ms
t_s	Start-up time (from V_I connection to 90% of V_{OI})				24	ms
t_{RC}	RC start-up time (from V_{RC} connection to 90% of V_{OI})	max I_O		1.5	10	ms
RC	Sink current	See operating information	10			mA
	Trigger level	Decreasing / Increasing RC-voltage		0.8/2.5		V
I_O	Output current		0		2.5	A
I_{lim}	Current limit threshold	$V_I = 24$ V, $T_{P1} < \max T_{P1}$		4.36	6.25	A
I_{sc}	Short circuit current	$T_{P1} = 25^\circ\text{C}$, see Note 1		0.05	0.1	A
C_{out}	Recommended Capacitive Load	$T_{P1} = 25^\circ\text{C}$, see Note 2	0		3000	µF
V_{Oac}	Output ripple & noise	See ripple & noise section, V_{OI}		15	150	mVp-p
OVP	Over voltage protection	$T_{P1} = +25^\circ\text{C}$, $V_I = 24$ V, 0-100% of max I_O		15		V

Note 1: hiccup mode

Note 2: Test condition: Electrolytic Capacitor and full load

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017


© Flex

Typical Characteristics


12 V, 2.5 A / 30 W

PKE 3313A PI


Efficiency




Power Dissipation



Output Current Derating



Current Limit Characteristics



PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W


1/ 28701- BMR 712 Rev. B November 2017

© Flex


Typical Characteristics 12 V, 2.5 A / 30 W

PKE 3313A PI


Start-up




Shut-down



Output Ripple & Noise



Output Load Transient Response



Output Voltage Adjust (TRIM UP/TRIM DOWN)

Output Voltage=12V

The resistor value for an adjusted output voltage is calculated by using the following equations:

Output Voltage Adjust, Increase:

$$R_{\text{ADJ_UP}} = \left(\frac{3.5998}{\Delta} - 27 \right) \text{ k}\Omega$$

Output Voltage Adjust, Decrease:

$$R_{\text{ADJ_DOWN}} = \left(\frac{3.5796}{\Delta} - 34.179 \right) \text{ k}\Omega$$

Example:

To trim up the 12V model by 8% to 12.96V the required external resistor is:

$$R_{\text{ADJ_UP}} = \left(\frac{3.5998}{0.08} - 27 \right) = 18 \text{ k}\Omega$$

Example:

To trim down the 12V model by 7% to 11.16V the required external resistor is:

$$R_{\text{ADJ_DOWN}} = \left(\frac{3.5796}{0.07} - 34.179 \right) = 16.96 \text{ k}\Omega$$

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W


1/ 28701- BMR 712 Rev. B November 2017

© Flex

EMC Specification

Conducted EMI measured according to EN55022, CISPR 22 and FCC part 15J. See Design Note 029 for further information. The fundamental switching frequency is 350 kHz for PKE 3313A PI (12V/30W) at $V_I = 24$ V and max I_O .



Conducted EMI Input terminal value (typ)




EMI without filter

Optional external filter for class B

Suggested external input filter in order to meet class B in EN 55022, CISPR 22 and FCC part 15J.



EMI with filter



Test set-up


Layout recommendations

The radiated EMI performance of the product will depend on the PWB layout and ground layer design. It is also important to consider the stand-off of the product.

A ground layer will increase the stray capacitance in the PWB and improve the high frequency EMC performance.

Output ripple and noise

Output ripple and noise measured according to figure below.



Output ripple and noise test setup

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Operating information**Input Voltage**

The input voltage range is 9 to 36 Vdc.


At input voltages exceeding 36 V, the power loss will be higher than at normal input voltage and T_{P1} must be limited to absolute max +100°C. The absolute maximum continuous input voltage is 36 Vdc.

Short duration transient disturbances can occur on the DC distribution and input of the product when a short circuit fault occurs on the equipment side of a protective device (fuse or circuit breaker). The voltage level, duration and energy of the disturbance are dependant on the particular DC distribution network characteristics and can be sufficient to damage the product unless measures are taken to suppress or absorb this energy. The transient voltage can be limited by capacitors and other energy absorbing devices like zener diodes connected across the positive and negative input conductors at a number of strategic points in the distribution network. The end-user must secure that the transient voltage will not exceed the value stated in the Absolute maximum ratings. ETSI TR 100 283 examines the parameters of DC distribution networks and provides guidelines for controlling the transient and reduce its harmful effect.

Turn-off Input Voltage

The products monitor the input voltage and will turn on and turn off at predetermined levels.

The minimum hysteresis between turn on and turn off input voltage is about 1 V.

Remote Control (RC)

The products are fitted with a remote control function referenced to the primary negative input connection -In, with negative and positive logic options available. The RC function allows the product to be turned on/off by an external device like a semiconductor or mechanical switch. The RC pin has an internal pull up resistor to +In.

The external device must provide a minimum required sink current to guarantee a voltage not higher than maximum voltage on the RC pin (see Electrical characteristics table). When the RC pin is left open, the voltage generated on the RC pin is 3 – 6 V.

The standard product is provided with “negative logic” (Active Low) remote control. When the RC pin is left open, or connected to a voltage higher than 2V referenced to -In, the product will be off when the input voltage is applied. To turn on the product the RC pin should be connected to -In. In situations where it is desired to have the product to power up automatically without the need for control signals or a switch, the RC pin must be wired directly to -In.

The second option is “positive logic” (Active High) remote control, which can be ordered by adding the suffix “P” to the end of the part number. In this case, when the RC pin is left open, the product starts up automatically when the input voltage is applied. Turn off is achieved by connecting the RC pin to the -In. The product will restart automatically when this connection is opened.

See Design Note 021 for detailed information.

Input and Output Impedance

The impedance of both the input source and the load will interact with the impedance of the product. It is important that the input source has low characteristic impedance. The products are designed for stable operation without external capacitors connected to the input or output. The performance in some applications can be enhanced by addition of external capacitance as described under External Decoupling Capacitors.

If the input voltage source contains significant inductance, the addition of a 22 - 100 μ F capacitor across the input of the product will ensure stable operation. The capacitor is not required when powering the product from an input source with an inductance below 10 μ H. The minimum required capacitance value depends on the output power and the input voltage. The higher output power the higher input capacitance is needed.

External Decoupling Capacitors

When powering loads with significant dynamic current requirements, the voltage regulation at the point of load can be improved by addition of decoupling capacitors at the load. The most effective technique is to locate low ESR ceramic and electrolytic capacitors as close to the load as possible, using several parallel capacitors to lower the effective ESR. The ceramic capacitors will handle high-frequency dynamic load changes while the electrolytic capacitors are used to handle low frequency dynamic load changes. It is equally important to use low resistance and low inductance PWB layouts and cabling.

External decoupling capacitors will become part of the product's control loop. The control loop is optimized for a wide range of external capacitance and the maximum recommended value that could be used without any additional analysis is found in the Electrical specification.

The ESR of the capacitors is a very important parameter. Stable operation is guaranteed with a verified ESR value of $>5m\Omega$ across the output connections.

For further information please contact your local Flex representative.

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex


Output Voltage Adjust (V_{adj})

The products have an Output Voltage Adjust pin (V_{adj}). This pin can be used to adjust the output voltage above or below Output voltage initial setting.

When increasing the output voltage, the voltage at the output pins must be kept below the threshold of the over voltage protection, (OVP) to prevent the product from shutting down. At increased output voltages the maximum power rating of the product remains the same, and the max output current must be decreased correspondingly.

To increase the voltage the resistor should be connected between the V_{adj} pin and -Out pin. The resistor value of the Output voltage adjust function is according to information given under the Output section for the respective product.

To decrease the output voltage, the resistor should be connected between the V_{adj} pin and +Out pin.

**Over Temperature Protection (OTP)**

The products are protected from thermal overload by an internal over temperature shutdown circuit.

When T_{P1} as defined in thermal consideration section exceeds 110°C the product will shut down. The product will make continuous attempts to start up (non-latching mode) and resume normal operation automatically when the temperature has dropped >5°C below the temperature threshold.

Over Voltage Protection (OVP)

The products have output over voltage protection that will shut down the product in over voltage conditions. The product will make continuous attempts to start up (non-latching mode) and resume normal operation automatically after removal of the over voltage condition.

Over Current Protection (OCP)

The products include current limiting circuitry for protection at continuous overload. The output voltage will decrease towards zero for output currents in excess of max output current (max I_o). The product will resume normal operation after removal of the overload. The load distribution should be designed for the maximum output short circuit current specified.

PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017


© Flex

Thermal Consideration**General**

The products are designed to operate in different thermal environments and sufficient cooling must be provided to ensure reliable operation.


For products mounted on a PWB without a heat sink attached, cooling is achieved mainly by conduction, from the pins to the host board, and convection, which is dependant on the airflow across the product. Increased airflow enhances the cooling of the product. The Output Current Derating graph found in the Typical Characteristics section provides the available output current vs. ambient air temperature and air velocity at $V_I = 24$ V.

The product is tested on a 107 x 45 mm, 70 μ m (2 oz), 1-layer test board in a wind box of 370 x 220 mm.

**Definition of product operating temperature**

The product operating temperatures is used to monitor the temperature of the product, and proper thermal conditions can be verified by measuring the temperature at positions P1. The temperature at this position (T_{P1}) should not exceed the maximum temperatures in the table below. Temperature above maximum T_{P1} , measured at the reference point P1 are not allowed and may cause permanent damage.

Position	Description	Max Temp.
P1	Reference point	$T_{P1} = 100^\circ \text{C}$



PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Connections





Pin	Designation	Function
1	+Input	Positive input
2	-Input	Negative input
3	On/Off Control	Remote control
4	+Out	Positive output
5	-Out	Negative output
6	TRIM	Output voltage adjust

PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Mechanical Information



RECOMMENDED FOOTPRINT
TOP VIEW

Notes:

1. All dimensions in inches (mm)
2. Tolerance .xx = ±0.05"
xxx = ±0.020"

PIN CONNECTIONS	
PIN NUMBER	PIN FUNCTION
1	+Input
2	-Input
3	On/Off Control
4	+Output
5	-Output
6	Trim

PKE 3000A series Direct Converters

Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017


© Flex

Soldering Information - Hole Mounting

The hole mounted product is intended for plated through hole mounting by wave or manual soldering. The pin temperature is specified to maximum to 270°C for maximum 10 seconds.

A maximum preheat rate of 4°C/s and maximum preheat temperature of 150°C is suggested. When soldering by hand, care should be taken to avoid direct contact between the hot soldering iron tip and the pins for more than a few seconds in order to prevent overheating.

A no-clean flux is recommended to avoid entrapment of cleaning fluids in cavities inside the product or between the product and the host board. The cleaning residues may affect long time reliability and isolation voltage.

Delivery Package Information

PKE 3000A series Direct Converters
Input 9 - 36 V, Output up to 2.5 A / 30 W

1/ 28701- BMR 712 Rev. B November 2017

© Flex

Product Qualification Specification

Characteristics			
External visual inspection	IPC-A-610		
Change of temperature (Temperature cycling)	IEC 60068-2-14 Na	Temperature range Number of cycles Dwell/transfer time	-55 to 125°C 20 30 min/5 min
Damp heat	IEC 60068-2-30	Temperature Humidity Duration	55°C 95 % RH 72 hours
Electrostatic discharge susceptibility	IEC 61340-3-1, JESD 22-A114	Human body model (HBM)	Class 2, 2000 V
Mechanical shock	IEC 60068-2-27 Ea	Peak acceleration Duration	30 g 6 ms
Operational life test	MIL-STD-202G, method 108A	Duration	1000 h
Resistance to soldering heat ²	IEC 60068-2-20 Tb, method 1A	Solder temperature Duration	270°C 10-13 s
Robustness of terminations	IEC 60068-2-21 Test Ua1	Through hole mount products	All leads
Solderability	IEC 60068-2-20 test Ta ¹	Preconditioning Temperature, SnPb Eutectic Temperature, Pb-free	235°C 245°C
Vibration, broad band random	IEC 60068-2-64 Fh, method 1	Frequency Spectral density Duration	10 to 500 Hz 0.07 g ² /Hz 10 min in each direction

Notes

¹ Only for products intended for wave soldering (plated through hole products)